



## ZXM500.4 - 4channel MINI Amplifier

Our R&D team has been working long and hard to release the ZXM series amplifiers into the world market. These amplifiers are made to be as small as possible without compromising sound quality, power and functions. ZXM5004 is a 4 channel amplifier with total power 500W RMS. This equals to 4x80W RMS in 4 Ohm but the amplifier is stable into 2Ohm and then delivers 4x125W RMS. The 4channels can also be bridged into 2x250W RMS in 4Ohm. The amplifier comes with adjustable HP/ LP filters and also a switch to use 2ch input or 4h input low or high level. A lot work has gone into making these amps with low EMI emissions to not interfere in advanced electronics or FM signal.

### Technical

HP / LP Filters 43-400Hz  
 2Ohm Stable  
 Low-level input  
 High-level input on RCA cut-able RCA input included  
 Bridgeable 2x250W RMS!  
 Autostart on high-level or remote input  
 Limited power on ISO - More power with extra power cable  
 1M maximum cable with ISO cable 4 Ohm Load only (25A MAX)  
 Full power 48A Load 2Ohm load or 4Ohm Bridge  
 4-layer PCB  
 Low EMI with special circuit board design

### Current draw and power rating:

4 Ohm - 4x80Watt RMS at maximum 26A  
 2 Ohm - 4x125Watt RMS at maximum 46A  
 4 Ohm Bridge - 2x260Watt RMS at maximum 47A

### Accessories:

**ZXMISOT1** - ISO-T Harness ZXM 1M  
**ZXMSY** - Y cable for signal Micro-fit  
**ZXMSC5** - Speaker cable 5m for ZXM amplifier



Part Number	Description	EAN Code	Unit Weight	Masterpack Weight	Masterpack
ZXM5004	4Channel 4x80W RMS 4 Ohm	5056171543698	1	1,1	10